

WARSUG Department of Fire and Emergency Services Perth Listening Guide 2018

First: Pick a frequency from this list for the 6AR / 6IP Network Command channel. These are linked together so pick **one** that is strong and clear in your area. All Fire and rescue turnouts in the Perth area are on this channel.

Channels 1-99 are mid band (78MHz), 101-653 are high band (165MHz)

This channel is also live Internet streamed- see <http://tinyurl.com/dfes-frequencies>

Channel	Frequency	Location	Channel	Frequency	Location
380	165.1875	Red Hill (NE hills)	57	78.1250	Red Hill (NE hills)
371	163.6750	Canning Mills (SE hills)	55	78.1000	Canning Mills (SE hills)
205	162.9875	Greenmount (East hills)	263	162.6000	Two Rocks
377	164.6125	Wanneroo	53	78.0750	Wanneroo
373	163.8000	Gingin	52	78.0625	Gingin
372	163.7125	Bunbury / N'bridge tunnel	105	163.0875	Bindoon
220	164.3375	Jarrahdale	80 / 30	78.4125	Jarrahdale / Bindoon
317	164.8875	Guilderton	92	78.5625	Guilderton
217	164.3125	Pinjarra	6 / 56	78.1125	Lancelin / Pinjarra
379	165.0125	Bold Park City Beach	51	78.0500	Claremont
376	164.5125	Wooroloo	58	78.1375	Wooroloo
328	164.1125	Northam	24	78.3375	Northam
207	164.2750	Hacket's Gully	25	78.3500	Hacket's Gully
246	164.1625	Lancelin			

Next: For major incidents, listen for the channels being allocated. It will be one *command* channel and a number of *sector* channels. The *command* channel is usually a repeater channel between **101** and **400**, **1** and **45** or **59** and **73**. Most command channels are dual midband/highband repeaters linked together. Incidents managed by DPaW will use channels between **500** and **653**. Smaller incidents and miscellaneous comms use simplex channel "Command 1" - **467.7875MHz**.

Each *sector* is allocated a simplex channel between **46** and **49**, **96** and **99** or **354** and **365**. These simplex channels are also occasionally used as *command* channels. Comms with private and council resources (bulldozers, etc) on the fireground sector will usually use standard UHF CB.

Air support and their ground controllers use repeater channels **644** or **621** and air tactical simplex channels such as **368** or **369**.

For the frequencies of these channels and live Internet streams, see the WARSUG DFES guides at <http://tinyurl.com/dfes-frequencies>

Inter-agency communications (Police, Rescue 65, etc) uses simplex channel **220** "Emergency C UHF" – **469.4375MHz**